

COSM

USB



Powerhouse FX with Stompbox Simplicity

The affordable new ME-25 is packed with powerful BOSS features to make you sound like a pro, yet it's as fun and easy to use as a stompbox. The built-in SOUND LIBRARY gives you instant access to dozens of classic and modern effects. Simply choose a category, select a variation and play. Customize your sound with simple twists of the Drive, Tone and Volume knobs. With COSM® amp models onboard, plus Super Stack and Phrase Loop, the ME-25 is a dream processor for upstart guitarists who want great sound and ease of use.



- ▶ Powerful COSM® amp models and effects onboard, from classic to contemporary
- ▶ Super simple user-friendly interface
- ▶ SOUND LIBRARY provides extensive collection of ready-to-use tones; simply choose a category and select a variation
- ▶ Sounds can be instantly edited with the Drive, Tone, Level knobs and Expression pedal
- ▶ SUPER STACK adds immensely heavy low-end and punch
- ▶ Phrase Loop function with 38 seconds of recording time
- ▶ Functions as a USB audio interface
- ▶ Built-in AUX input for jamming along with external music devices (MP3/CD players, etc.)
- ▶ Runs on six AA batteries or AC adaptor
- ▶ Includes Cakewalk SONAR 8.5 LE software and dozens of audio loops, rhythms and songs for jamming or practice
- ▶ Free downloadable Librarian software



ME-25 Specifications

■ AD Conversion 24-bit + AF method** ■ DA Conversion 24-bit ■ Sampling Frequency 44.1 kHz
 ■ Memory 60 ■ Sound Library 60 ■ Sound Library Category CLEAN, CRUNCH, DRIVE, HEAVY, LEAD, EXTREME ■ Effect Type COMP/FX (Compressor/Effect): COMP, T.WAH, AC SIM, OD/DS (Overdrive/Distortion): BOOST, OD-1, T-SCREAM, BLUES, DIST, CLASSIC, MODERN, METAL, CORE, FUZZ, PREAMP: CLEAN, TWIN, TWEED, VO DRIVE, BG LEAD, MS VINTAGE, MS MODERN, 5150 DRIVE, R-FIER, ULTRA METAL, MODULATION: CHORUS, PHASER, FLANGER, ROTARY, UNI-V, TREMOLO, HARMONIST, OCTAVE, DELAY: 1-99ms, 100-990ms, 1000-6000ms, TAP, REVERB: ROOM, HALL, PEDAL FX (Pedal Effect): WAH, +1 OCTAVE, -1 OCTAVE, FREEZE, NS (Noise Suppressor) ■ Nominal Input Level INPUT: -10 dBu, AUX IN: -18 dBu ■ Input Impedance INPUT: 1M , AUX IN: 22k ■ Nominal Output Level -10 dBu ■ Output Impedance 2k ■ Display 7 segments, 2 digits LED ■ Power Supply DC 9 V Dry Batteries (R6/LR6 (AA) type) x 6, AC Adaptor (BOSS PSA-Series: sold separately) ■ Current

Draw 150 mA ■ Expected battery life under continuous use Alkaline: 9 hours, Carbon: 3 hours (These figures will vary depending on the actual conditions of use.) ■ Dimensions 300 (W) x 191 (D) x 72 (H) mm/ 11-13/16 (W) x 7-9/16 (D) x 2-7/8 (H) inches ■ Maximum height 300 (W) x 191 (D) x 93 (H) mm/ 11-13/16 (W) x 7-9/16 (D) x 3-11/16 (H) inches ■ Weight 1.9 kg, 4 lbs 4 oz (including batteries)
 ■ Accessories Owner's Manual, ME-25 DVD-ROM, Sound Library/Memory List (Leaflet), Sound Library Sticker, Dry Batteries (Alkaline: LR6 (AA) type) x 6, Roland Service (Information Sheet) ■ Options AC Adaptor BOSS PSA-Series

* 1 AF method (Adaptive Focus method) / This is a proprietary method from Roland & BOSS
<http://acctest.ru/cat/protektor-effektor/>

* 0 dBu = 0.775 Vrms

* The specifications are subject to change without notice.